

Changes to legislation: There are currently no known outstanding effects for the Weights and Measures Act 1985, SCHEDULE 1. (See end of Document for details)

SCHEDULES

SCHEDULE 1

Sections 1(2), 8(1).

DEFINITIONS OF UNITS OF MEASUREMENT

PART I

MEASUREMENT OF LENGTH

Imperial units

F1	F1
...	...
F1	F1
...	...
F1	F1
...	...
F1	F1
...	...

Textual Amendments

F1 Sch. 1 Pts. I, II: entries omitted (1.10.1995) by virtue of [S.I. 1994/2867, reg. 6\(5\)\(a\)](#)

Metric units

Kilometre =	1000 metres.
METRE	[^{F2} for which the symbol “m” is used, is the SI unit of length, defined by taking the fixed numerical value of the speed of light in vacuum c to be 299 792 458 when expressed in the unit m/s, where the second is defined by taking the fixed numerical value of the caesium frequency $\Delta\nu_{\text{Cs}}$, the unperturbed ground-state hyperfine transition frequency of the caesium 133 atom, to be 9 192 631 770 when expressed in the unit Hz, which is equal to s^{-1} .]
Decimetre =	1/10 metre.

*Changes to legislation: There are currently no known outstanding effects for the
 Weights and Measures Act 1985, SCHEDULE 1. (See end of Document for details)*

Centimetre =	1/100 metre.
Millimetre =	1/1000 metre.

Textual Amendments

F2 Words in Sch. 1 Pt. 1 substituted (13.6.2020) by [The Weights and Measures Act 1985 \(Definitions of Metre and Kilogram\) \(Amendment\) Order 2020 \(S.I. 2020/586\)](#), arts. 1(b), **2(2)**

PART II

MEASUREMENT OF AREA

Imperial units

F3	F3
...	...
F3	F3
...	...
F3	F3
...	...

Textual Amendments

F3 Sch. 1 Pts. I, II: entries omitted (1.10.1995) by virtue of [S.I. 1994/2867, reg. 6\(5\)\(a\)](#)

Metric units

Hectare =	100 ares.
Decare =	10 ares.
Are =	100 square metres.
SQUARE METRE=	a superficial area equal to that of a square each side of which measures one metre.
Square decimetre =	1/100 square metre.
Square centimetre =	1/100 square decimetre.
Square millimetre =	1/100 square centimetre.

Changes to legislation: There are currently no known outstanding effects for the Weights and Measures Act 1985, SCHEDULE 1. (See end of Document for details)

PART III

MEASUREMENT OF VOLUME

Metric units

CUBIC METRE =	a volume equal to that of a cube each edge of which measures one metre.
Cubic decimetre =	1/1000 cubic metre.
Cubic centimetre =	1/1000 cubic decimetre.
Hectolitre =	100 litres.
LITRE =	a cubic decimetre.
Decilitre =	1/10 litre.
Centilitre =	1/100 litre.
Millilitre =	1/1000 litre.

PART IV

MEASUREMENT OF CAPACITY

[^{F4}Imperial unit]

Textual Amendments

F4 Heading in Sch. 1 Pt. IV substituted (1.1.2000) by [S.I. 1994/2867, reg. 7\(3\)\(a\)\(i\)](#)

F5	F5
...	...
F5	F5
...	...
Pint =	[^{F6} 0.568 261 25 cubic decimetre.]
F5	F5
...	...
F7	F7
...	...

Textual Amendments

F5 Sch. 1 Pt. IV: definitions of “gallon”, “quart” and “gill” omitted (1.10.1995) by virtue of [S.I. 1994/2867, reg. 6\(5\)\(b\)\(i\)](#)

F6 Sch. 1 Pt. IV: definition substituted (1.10.1995) by [S.I. 1994/2867, reg. 6\(5\)\(b\)\(ii\)](#)

Changes to legislation: There are currently no known outstanding effects for the Weights and Measures Act 1985, SCHEDULE 1. (See end of Document for details)

F7 Sch. 1 Pt. IV: definition of “fluid ounce” omitted (1.1.2000) by virtue of [S.I. 1994/2867, reg. 7\(3\)\(a\)\(ii\)](#)

Metric units

Hectolitre =	100 litres.
LITRE =	a cubic decimetre.
Decilitre =	1/10 litre.
Centilitre =	1/100 litre.
Millilitre =	1/1000 litre.

PART V

MEASUREMENT OF MASS OR WEIGHT

[^{F8}Imperial unit]

Textual Amendments

F8 Heading in Sch. 1 Pt. V substituted (1.1.2000) by [S.I. 1994/2867, reg. 7\(3\)\(b\)\(i\)](#)

F9	F9
...	...
F9	F9
...	...
[^{F10}OUNCE TROY=]	[^{F10}0.031 103 476 8 kilogram.]

Textual Amendments

F9 Sch. 1 Pt. V: definitions of “pound” and “ounce” omitted (1.1.2000) by virtue of [S.I. 1994/2867, reg. 7\(3\)\(b\)\(ii\)](#)

F10 Sch. 1 Pt. V: definition of “ounce troy” substituted (1.1.2000) by [S.I. 1994/2867, reg. 7\(3\)\(b\)\(iii\)](#)

Metric units

Tonne, metric tonne =	1000 kilograms.
KILOGRAM	^{F11} for which the symbol “kg” is used, is the SI unit of mass, defined by taking the fixed numerical value of the Planck constant h to be $6.626\ 070\ 15 \times 10^{-34}$ when expressed in the unit J s, which is equal to kg m^2

Changes to legislation: There are currently no known outstanding effects for the Weights and Measures Act 1985, SCHEDULE 1. (See end of Document for details)

	s^{-1} , where the second is defined by taking the fixed numerical value of the caesium frequency $\Delta\nu_{Cs}$, the unperturbed ground-state hyperfine transition frequency of the caesium 133 atom, to be 9 192 631 770 when expressed in the unit Hz, which is equal to s^{-1} .]
Hectogram =	1/10 kilogram.
Gram =	1/1000 kilogram.
Carat (metric) =	1/5 gram.
Milligram =	1/1000 gram.

Textual Amendments

F11 Words in Sch. 1 Pt. 5 substituted (13.6.2020) by [The Weights and Measures Act 1985 \(Definitions of Metre and Kilogram\) \(Amendment\) Order 2020 \(S.I. 2020/586\)](#), arts. 1(b), **2(3)**

[^{F12}PART VI

DEFINITIONS OF CERTAIN UNITS WHICH MAY NOT BE USED FOR TRADE EXCEPT AS SUPPLEMENTARY INDICATIONS

Textual Amendments

F12 Sch. 1 Pt. VI substituted (1.10.1995) by [S.I. 1994/2867](#), reg. **6(5)(c)**

			Measurement of length
Mile	=	1760 yards.	
Furlong	=	220 yards.	
Chain	=	22 yards.	
YARD	=	0.9144 metre.	
Foot	=	1/3 yard.	
Inch	=	1/36 yard.	
			Measurement of area
Square mile	=	640 acres.	
Acre	=	4840 square yards.	
Rood	=	1210 square yards.	
Square yard	=	a superficial area equal to that of a square each side of which measures one yard.	

Changes to legislation: There are currently no known outstanding effects for the Weights and Measures Act 1985, SCHEDULE 1. (See end of Document for details)

Square foot	=	1/9 square yard.
Square inch	=	1/144 square foot.

Measurement of volume

Cubic yard	=	a volume equal to that of a cube each edge of which measures one yard.
Cubic foot	=	1/27 cubic yard.
Cubic inch	=	1/1728 cubic foot.

Measurement of capacity

Bushel	=	8 gallons.
Peck	=	2 gallons
GALLON	=	4.54609 cubic decimetres.
Quart	=	¼ gallon.
Gill	=	¼ pint.
[^{F13} Fluid ounce]	[^{F13} =]	[^{F13} 1/20 pint.]
Fluid drachm	=	1/8 fluid ounce.
Minim	=	1/60 fluid drachm.

Measurement of mass or weight

Ton	=	2240 pounds.
Hundredweight	=	112 pounds.
Cental	=	100 pounds.
Quarter	=	28 pounds.
Stone	=	14 pounds.
[^{F14} POUND]	[^{F14} =]	[^{F14} 0.453 592 37 kilogram.]
[^{F15} Ounce]	[^{F15} =]	[^{F15} 1/16 pound]
Dram	=	1/16 ounce.
Grain	=	1/7000 pound.
Pennyweight	=	24 grains.
Ounce apothecaries	=	480 grains.
Drachm	=	1/8 ounce apothecaries.
Scruple	=	1/3 drachm.
Metric ton	=	1000 kilograms.
Quintal	=	100 kilograms.]

Changes to legislation: There are currently no known outstanding effects for the Weights and Measures Act 1985, SCHEDULE 1. (See end of Document for details)

Textual Amendments

F13 Sch. 1 Pt. VI: definition of “fluid ounce” inserted (1.1.2000) by S.I. 1994/2867, reg. 7(3)(c)(i)

F14 Sch. 1 Pt. VI: definition of “pound” inserted (1.1.2000) by S.I. 1994/2867, reg. 7(3)(c)(ii)

F15 Sch. 1 Pt. VI: definition of “ounce” inserted (1.1.2000) by S.I. 1994/2867, reg. 7(3)(c)(ii)

Textual Amendments

F13 Sch. 1 Pt. VI: definition of “fluid ounce” inserted (1.1.2000) by S.I. 1994/2867, reg. 7(3)(c)(i)

F14 Sch. 1 Pt. VI: definition of “pound” inserted (1.1.2000) by S.I. 1994/2867, reg. 7(3)(c)(ii)

F15 Sch. 1 Pt. VI: definition of “ounce” inserted (1.1.2000) by S.I. 1994/2867, reg. 7(3)(c)(ii)

PART VII

MEASUREMENT OF ELECTRICITY

1. (a) AMPERE [F16 for which the symbol “A” is used, is the SI unit of electric current, defined by taking the fixed numerical value of the elementary charge e to be 1.602 176 634 $\times 10^{-19}$ when expressed in the unit C, which is equal to A s, where the second is defined by taking the fixed numerical value of the caesium frequency $\Delta\nu_{\text{Cs}}$, the unperturbed ground-state hyperfine transition frequency of the caesium 133 atom, to be 9 192 631 770 when expressed in the unit Hz, which is equal to s^{-1} .]
- (b) OHM is the electric resistance between two points of a conductor when a constant potential difference of 1 volt, applied between the two points, produces in the conductor a current of 1 ampere, the conductor not being the seat of any electromotive force.
- (c) VOLT is the difference of electric potential between two

*Changes to legislation: There are currently no known outstanding effects for the
Weights and Measures Act 1985, SCHEDULE 1. (See end of Document for details)*

		<p>points of a conducting wire carrying a constant current of 1 ampere when the power dissipated between these points is equal to 1 watt.</p>
	(d) WATT	<p>is the power which in one second gives rise to energy of 1 joule [^{F17}, where the second has the meaning given in the definition of “AMPERE”].</p>
2.	Kilowatt	= 1000 watts.
	Megawatt	= one million watts.

Textual Amendments

- F16** Words in Sch. 1 Pt. 7 substituted (13.6.2020) by [The Weights and Measures Act 1985 \(Amendment\) and Units of Measurement Regulations 1986 \(Amendment\) Regulations 2019 \(S.I. 2019/1211\)](#), regs. 1(b), 2(a)
- F17** Words in Sch. 1 Pt. 7 inserted (13.6.2020) by [The Weights and Measures Act 1985 \(Amendment\) and Units of Measurement Regulations 1986 \(Amendment\) Regulations 2019 \(S.I. 2019/1211\)](#), regs. 1(b), 2(b)

Changes to legislation:

There are currently no known outstanding effects for the Weights and Measures Act 1985, SCHEDULE 1.